

Amendments to the Claims

Please cancel Claims 41, 44, 47, and 50. Please amend Claims 1, 17, 25, 32, 34, 40, and 52. The Claim Listing below will replace all prior versions of the claims in the application:

Claim Listing

1. (Currently Amended) A method for determining, in an electrical signal, a presence of sinusoids used to encode dialed digits, the method comprising:
splitting the electrical signal into subbands being at a sampling frequency of about 2 kHz ~~a highest frequency of the sinusoids~~; and
analyzing energies within the subbands to determine the presence of the sinusoids.
2. (Original) The method according to Claim 1, wherein splitting the electrical signal into the subbands comprises extracting subbands of 0-1 kHz and 1-2 kHz.
3. (Original) The method according to Claim 1, wherein splitting the electrical signal into the subbands comprises filtering the electrical signal using a power symmetric infinite impulse response (PS-IIR) filter.
4. (Original) The method according to Claim 3, wherein the PS-IIR filters are implemented in a polyphase form.
5. (Original) The method according to Claim 3, wherein the PS-IIR filters comprise all-pass sections implemented in compact realizations.
6. (Original) The method according to Claim 1, further comprising filtering the subbands with at least one bank of filters comprising filters corresponding to the number of possible frequencies of the sinusoids within the respective subbands.
7. (Original) The method according to Claim 6, wherein the filters are notch filters.

8. (Original) The method according to Claim 6, wherein, for DTMF detection, splitting the electrical signal comprises (i) extracting a 0-1 kHz subband and a 1-2 kHz subband and (ii) filtering the subbands with four notch filters per bank of filters.
9. (Original) The method according to Claim 6, wherein, for MF-R1 detection, splitting the electrical signal comprises (i) extracting a 0-1 kHz subband and a 1-2 kHz subband and (ii) filtering the 0-1 kHz subband with two notch filters and the 1-2 kHz subband with four notch filters.
10. (Original) The method according to Claim 6, wherein:
for MF-R2 forward detection, splitting the electrical signal comprises (i) extracting a 0-1 kHz subband and 1-2 kHz subband and (ii) filtering the 1-2 kHz subband with six notch filters; and
for backward detection, splitting the electrical signal comprises (i) extracting a 0-1 kHz subband and a 1-2 kHz subband and (ii) filtering the 0-1 kHz subband with a notch filter at 980 Hz, to remove aliasing of a 1020 Hz tone in the 1-2 kHz subband, and four other notch filters and the 1-2 kHz subband with two notch filters.
11. (Original) The method according to Claim 6, further comprising preclassifying the sinusoids in the subbands and selecting filters within respective banks of filters that match frequencies of the preclassified sinusoids.
12. (Original) The method according to Claim 1, wherein analyzing the energies comprises determining whether a summing of the energies in the subbands exceeds a minimum threshold level.

C1

SUB
DI

- C/
13. (Original) The method according to Claim 1, wherein analyzing the energies comprises determining whether a difference between the energies in the subbands is below a twist-test threshold.
14. (Original) The method according to Claim 1, wherein for each subband, analyzing the energies comprises comparing energy levels of an output of a notch filter having a lowest output energy level from among at least two notch filters in a bank of filters to the energy of the input signal to the bank of filters.
15. (Original) The method according to Claim 1, wherein analyzing the energies further comprises reporting valid dialed digits.
16. (Original) The method according to Claim 1, wherein the electrical signal is sampled by an analog-to-digital converter and splitting and analyzing the electrical signal is executed by a digital processor.
17. (Currently Amended) An apparatus, comprising:
a splitter to separate an electrical signal, including sinusoids corresponding to frequencies of dialed digits, into subbands being at a sampling frequency of about 2 kHz a highest frequency of the sinusoids; and
an analyzer to measure energies within the subbands to determine a presence of the sinusoids.
18. (Original) The apparatus according to Claim 17, wherein the splitter extracts subbands of 0-1 kHz and 1-2 kHz.
19. (Original) The apparatus according to Claim 17, wherein the splitter comprises a power symmetric infinite impulse response (PS-IIR) filter to separate the signal into subbands.

20. (Original) The apparatus according to Claim 17, further comprising at least one bank of filters to filter the subbands, the bank of filters comprising filters corresponding to the number of possible frequencies of sinusoids within the respective subbands.
21. (Original) The apparatus according to Claim 20, wherein the filters are notch filters.
22. (Original) The apparatus according to Claim 20, further comprising at least one preclassifier to determine the sinusoids in the subbands and to select filters within respective banks of filters that match frequencies of the sinusoids.
23. (Original) The apparatus according to Claim 17, wherein the electrical signal is sampled by an analog-to-digital converter and the splitter and analyzer are implemented in digital processor instructions and executed by a digital processor.
24. (Original) The apparatus according to Claim 17 being employed in a device supporting voice-over-IP.
25. (Currently Amended) An apparatus, comprising:
an analog-to-digital converter sampling a received analog signal, including sinusoids corresponding to frequencies of dialed digits, and outputting a corresponding digital signal; and
a digital processor coupled to an output of the analog-to-digital converter to receive the digital signal, the digital signal processor executing program instructions to:
split the digital signal into subbands being at a sampling frequency of about 2 kHz ~~a highest frequency of the sinusoids~~; and
analyze energies within the subbands to determine a presence of the sinusoids.

C1

~~23~~SCU3
DI

26. (Original) The apparatus according to Claim 25, wherein the program instructions to split the digital signal into subbands comprise instructions to extract subbands of 0-1 kHz and 1-2 kHz.
27. (Original) The apparatus according to Claim 25, wherein the program instructions to split the electrical signal into the subbands comprise instructions to filter the electrical signal using a power symmetric infinite impulse response (PS-IIR) filter.
28. (Original) The apparatus according to Claim 25, further comprising program instructions to filter the subbands with at least one bank of filters comprising filters corresponding to the number of possible frequencies of sinusoids within the respective subbands.
29. (Original) The apparatus according to Claim 28, wherein the filters are notch filters.
30. (Original) The apparatus according to Claim 28, further comprising program instructions to preclassify the sinusoids in the subbands and select filters within respective banks of filters that match frequencies of the preclassified sinusoids.
31. (Original) The apparatus according to Claim 25 employed in a device supporting voice-over-IP.
32. (Currently Amended) An apparatus, comprising:
means for splitting an electrical signal, including sinusoids corresponding to frequencies of dialed digits, into subbands being at a sampling frequency of about 2 kHz ~~a highest frequency of the sinusoids~~; and
means for analyzing energies within the subbands to determine a presence of the sinusoids.
33. (Original) The apparatus according to Claim 32 employed in a device supporting voice-over-IP.

C1
SUB
31

34. (Currently Amended) A computer-readable medium having stored thereon sequences of instructions, the sequences of instructions including instructions, when executed by a processor, causes the processor to perform:
- splitting an electrical signal, including sinusoids corresponding to frequencies of dialed digits, into subbands being at a sampling frequency of about 2 kHz ~~a highest frequency of the sinusoids~~; and
- analyzing energies within the subbands to determine a presence of the sinusoids.
35. (Original) The computer-readable medium of Claim 34, wherein splitting the electrical signal into subbands comprises extracting subbands of 0-1 kHz and 1-2 kHz.
36. (Original) The computer-readable of Claim 34, wherein splitting the electrical signal into subbands comprises filtering the electrical signal using a power symmetric infinite impulse response (PS-IIR) filter.
37. (Original) The computer-readable medium of Claim 34, further comprising instructions which, when executed by the processor, causes the processor to filter the subbands with at least one bank of filters comprising filters corresponding to the number of possible frequencies of sinusoids within the respective subbands.
38. (Original) The computer-readable medium of Claim 37, wherein the filters are notch filters.
39. (Original) The computer-readable medium of Claim 37, further comprising instructions which, when executed by the processor, causes the processor (i) to preclassify the sinusoids in the subbands and (ii) to select filters within respective banks of filters that match frequencies of the preclassified sinusoids.
40. (Currently Amended) A voice-over-IP device, comprising:

a receiver receiving electrical signals composed of voice signals and dialed digit sinusoids corresponding to dialed digits;

a detector coupled to the receiver to monitor the electrical signals and to detect the dialed digit sinusoids, said detector including:

a splitter to split the electrical signal into subbands being at a sampling frequency of about 2 kHz ~~a highest frequency of the sinusoids~~;

an analyzer to analyze energies within subbands to determine a presence of the sinusoids; and

a generator to generate packets of data comprising (i) voice signal data and (ii) information corresponding to the dialed digits.

41. (Cancelled)

42. (Previously Presented) The method according to Claim 1 wherein splitting the electrical signal is performed at about the highest frequency of the sinusoids.

43. (Previously Presented) The method according to Claim 1 wherein analyzing the energies is performed at about the highest frequency of the sinusoids.

44. (Cancelled)

45. (Previously Presented) The apparatus according to Claim 17 wherein the splitter operates at about the highest frequency of the sinusoids.

46. (Previously Presented) The apparatus according to Claim 17 wherein the analyzer operates at about the highest frequency of the sinusoids.

47. (Cancelled)

48. (Previously Presented) The apparatus according to Claim 25 wherein the program instructions to split the digital signal into subbands split the digital signal at about the highest frequency of the sinusoids.
49. (Previously Presented) The apparatus according to Claim 25 wherein the program instructions to analyze the energies of the digital signal analyze the energies at about the highest frequency of the sinusoids.
50. (Cancelled)
51. (Previously Presented) The computer-readable medium of Claim 34 wherein splitting the electrical signal is performed at about the highest frequency of the sinusoids.
52. (Currently Amended) The computer-readable medium of Claim 34 wherein analyzing the energies is performed at about the highest frequency of the sinusoids.